

Part # IL-60W-3W-230

LED DRIVER

60 WATT 3 WIRE DIMMING

3 WIRE



Current Sourcing

Dims to .03 on 100-Step Scale

PRODUCT SPECIFICATIONS

60 Watt, 3 Wire Full-Range Dimming
LED Class 2 Power Supply

60W 12V DC Constant Voltage

Input Voltage Options:

- 120V 50/60Hz
- 230V 50Hz

Dimming Circuits: Isolated

Over-Current Shut Down Auto Reset

Over-Heat Protection Auto Reset

Built-In Heat Sinks

Works with Other Light Fixtures
on Same Dimmer

Smooth Dimming Transition, No "Pop-On"

In-Rush Start Up, 14 Amps at 2 Milliseconds

UL No. E469630

Schematics not to scale.



22.8125" (579.44mm)

2.50"
63.50mm

